EE4800/EE5880 Real Time Embedded Systems

Lesson 21-24


Fuzzy Logic

Overview

- What is a control system?
- Traditional vs Fuzzy Logic Control Systems
- Fuzzy Logic Controller Overview
- 68HC12 Fuzzy Logic Operations
- Membership Function Design Process
- Fuzzy Rule Implementation
- 68HC12 Fuzzification Process
- Rule Evaluation
- 68HC12 Defuzzification Process
- Mobile Robot Example

What is a control system?

- Any system, whose outputs are controlled by some inputs to the system, is called a control system
- Typical control system, Figure 4.1, pg 120



What is a control system?


- Uses model along with feedback provided by system output to generate a new system input
- Controller requires accurate mathematical model of system
 - Requires dynamic equations
 - Euler Lagrange Equation Ref. Section 4.2.2.
 - Not fun stuff!!!

Traditional vs Fuzzy Logic Control Systems

- Traditional control method requires accurate, often complex system of equations
- Fuzzy logic proponents claim fuzzy systems are much closer to human control process
- Neural networks, fuzzy logic, and evolutionary systems share common thread
 - Do not rely on mathematical systems descriptions
- Interestingly, biological control systems do not rely on complex mathematical models
- Traditional camp treats these new approaches with skepticism for lack of mathematical rigor
- Fuzzy logic controllers in heavy use

Fuzzy Logic Controller Overview


- Fuzzy Logic Control Systems rely on physical rules rather than mathematical equations
- Simple form of an expert system
- Expert system contains rules that map input commands to output system responses
- Also an evidence accumulating system
 - Uses confidence factor to assign a system output according to the confidence measure computed using a well-defined process




- Inputs should be sufficient to describe current status of system
- Need appropriate relationships between inputs and outputs
- Represent output control values in suitable form for system control

- Input values are first fuzzified by assigning an appropriate value (degree of membership) to each fuzzy membership function
- Fuzzy membership function is defined as an instance of a linguistic variable describing the fuzzy controller input
- All fuzzy membership functions have one of the following shapes: a left trap (LT), a trapezoid (TR) and a right trap (RT)

- HC12 implements all of its input membership functions using trapezoids
- Fig 4.5, page 128



- Given an input datum, the controller must first assign a degree of membership, a value ranging from zero to one, to each fuzzy membership function.
- Fig. 4.6, pg 129



10


- Apply expert rules to input membership functions
- Rules should cover all possible combinations of the input variables
- Rules map combinations of inputs to output force fuzzy membership functions
- Rule format:

If (antecedent 1) AND (antecedent 2), Then (desired response)

- In applying rules, the **minimum** degree of membership among the input functions is assigned to the output membership function
 - Known as minimum rule
- Forms confidence factor
- Minimum of the two is chosen since it guarantees that both antecedents are true


- Controller now takes the maximum of the confidence factors as the degree of the membership for the particular fuzzy function.
- Relies on the most dominant rule to assign the output membership function
- Need to convert the output membership function values to a form suitable to control system
 - Control value must be a numerical one
 - Need to reverse process of fuzzification defuzzification

- Defuzzification most common method is finding center of gravity or centroid of output membership functions
 - Combines all regions of the output fuzzy functions with OR operator
 - Computes center point
 - Generates crisp numerical value
- Gives equal weights to each output membership function



- Four 68HC12 instructions:
 - MEM: grade of membership
 - REV: MIN-MAX rule evaluation
 - REVW: MIN-MAX rule evaluation with optional rule weighting
 - WAV: performs weighted average calculations
- Supplementary instructions:
 - ETBL, TBL, EDIV, EDIVS, EMACS, EMAX, EMAXM, EMIND, EMINM, EMUL, EMULS

• Example: Design a fuzzy logic based robot controller - Fig 4.15, pg 149



Revised: Sep 1, 2004 17

1 . Determine linguistic variables describing all inputs to the controller

left sensor input: very weak, weak, medium, strong, very strong right sensor input: very weak, weak, medium, strong, very strong

2 . Each linguistic variable must be defined with a set of input membership functions. For the HC12 a trapezoidal function must be used. Fig 4.16, pg 150

Revised: Sep 1, 2004

18

- 3 . Input membership function design process.
 - Each membership function must be trapezoid: LT, T, RT
 - Specify uniquely with farthest left point, farthest right point, left slope, and right slope
 - Full membership corresponds to \$FF for each sensor

```
      very weak
      $00, $50, $00, $10

      weak
      $40, $70, $10, $10


      medium
      $60, $A0, $10, $10

      strong
      $90, $C0, $10, $10

      very strong
      $B0, $FF, $10, $00
```

- 4 . Output membership function design process.
- Use singleton functions for the fuzzy output membership functions (Singleton: each function is defined by a single value).
 - *Medium Left (\$40)*
 - Small Left (\$60)
 - Zero (\$80)
 - Small Right (\$A0)
 - *Medium Right (\$C0)*
 - **Assumption:** \$80 keeps robot on straight path.

Figure 4.17, pg 151



5. Determine fuzzy rules that map input to output membership functions. Rules are intuitive based on considering all possible input sensor value scenarios.

Rule format:

IF (antecedent 1) AND (antecedent 2), THEN (desired output)

Fuzzy Rules for Navigating Robot

Left/Right	Very	Strong	Medium	Weak	Very
_	Strong	_			Weak
Very	Zero	Small	Small	Medium	Medium
Strong		Right	Right	Right	Right
Strong	Small	Zero	Small	Medium	Medium
	Left		Right	Right	Right
Medium	Small	Small	Zero	Small	Small
	Left	Left		Right	Right
Weak	Medium	Medium	Small	Zero	Small
	Left	Left	Left		Right
Very	Medium	Medium	Small	Small	Zero
Weak	Left	Left	Left	Left	

Revised: Sep 1, 2004 22

6. Fuzzy Rule Implementation - encode rules for all input combinations using the format:

RULE 1:

antecedent one, antecedent two, \$FE, desired output, \$FE

Note: \$FE separator indicates convenient break points from fuzzy logic processing should an interrupt occur.

- 7. Deffuzify: Combine truth values of all output fuzzy membership functions into a single numerical value.
 - Average the output function values find the centroid of arbitrary output membership functions for singleton output membership functions.

Output =
$$\sum (Si Fi) / \sum (Fi)$$
 for $i = i ...n$

where: Si is the Singleton value

Fi is the output membership value for fuzzy logic output

function i

```
Line 1
      Line 2
      ; Fuzzy Logic Controller for A Mobile Robot
Line 3
      ; Description: This program takes in two Infrared
Line 4
      ; sensor values and computes a di-
Tine 5
      ; rection control signal to avoid
Tine 6
      ; wall collisions. The two sensor
Line 7 ; values are read from memory
Line 8 ;locations $6000 and $6001 and
Line 9 ; the control output value is
Line 10 ; written to memory location $6002
Line 11 :
Line 12 : Authors: Daniel Pack and Steve Barrett
Line 13 ; Date: 8-21-2000
```

```
Line 15 ; Data Section
Line 16 O R VS
                            $00 ;Offset values input and output mem fns
                      EQU
Line 17 O R ST
                            $01 ; Right Sensor Strong
                      EQU
Line 18 O R ME
                           $02 ; Right Sensor Medium
                      EQU
Line 19 O R WE
                           $03 ; Right Sensor Weak
                     EQU
Line 20 O R VW
                           $04 ; Right Sensor Very Weak
                   EQU
                           $05 ; Left Sensor Very Strong
Line 21 O L VS
                   EQU
Line 22 O L ST
                   EQU
                           $06 ; Left Sensor Strong
                           $07 ; Left Sensor Medium
Line 23 O L ME
                     EQU
Line 24 O L WE
                           $08 ; Left Sensor Weak
                   EQU
Line 25 O L VW
                           $09 ; Left Sensor Very Weak
                   EQU
Line 26 O ML
                           $0A ; Medium Left
                      EQU
Line 27 O SL
                           $0B ; Small Left
                      EQU
Line 28 O ZR
                            $0C ; Zero
                      EQU
                            $0D ; Small Right
Line 29 O SR
                      EQU
Line 30 O MR
                            $0E ; Medium Right
                   EQU
Line 31 MARKER
                            $FE ; rule separator
                      EQU
Line 32 ENDR
                            $FF ; end of rule marker
                      EQU
```

```
$6000
Line 33
                     ORG
Line 34 RSENSOR
                          $01 ; Allocating
                  RMB
                          $01 ; memory locations
Line 35 LSENSOR
                  RMB
Line 36 CONTROLS RMB
                          $01 ; for input/output variables
Line 37 ; Fuzzy Input Membership Function Definitions for Right Sensor
Line 38 R Very Strong FCB $B0, $FF, $10, $00
Line 39 R Strong FCB $90, $C0, $10, $10
Line 40 R_Medium FCB $60, $A0, $10, $10
Line 41 R Weak FCB $40, $70, $10, $10
Line 42 R Very Weak FCB $00, $50, $00, $10
Line 43 ; Fuzzy Input Membership Function Definitions for Left Sensor
Line 44 L Very Strong FCB $B0,$FF,$10,$00
Line 45 L Strong FCB $90,$C0,$10,$10
Line 46 L Medium FCB $60,$A0,$10,$10
Line 47 L Weak FCB $40,$70,$10,$10
Line 48 L Very Weak FCB $00,$50,$00,$10
```

```
Line 49 ; Fuzzy Output Membership Function Definitions
Line 50 Medium Left FCB
                          $40
Line 51 Small_Left FCB $60
Line 52 Zero FCB $80
Line 53 Small Right FCB $A0
Line 54 Medium Right FCB $C0
Line 55 ; Locations for fuzzy membership values
Line 56 R VS
                     RMB
                          $01
Line 57 R ST
                          $01
                 RMB
Line 58 R ME
                 RMB $01
Line 59 R WE
           RMB $01
Line 60 R VW
                    RMB
                          $01
Line 61 L VS
                    RMB
                          $01
Line 62 L ST
                          $01
            RMB
Line 63 L ME
                          $01
                    RMB
Line 64 L WE
                     RMB
                          $01
Line 65 L VW
                          $01
                     RMB
```

```
Line 66 ; Output Fuzzy Logic Membership Values - initialize them to zero
Line 67 ML
                               $00
                         FCB
Line 68 SL
                               $00
                         FCB
                               $00
Line 69 ZR
                         FCB
Line 70 SR
                         FCB
                               $00
Line 71 MR
                               $00
                         FCB
```

Revised: Sep 1, 2004

29

Line	72	; Rule Definitions		
Line	73	Rule_Start	FCB	O_R_VS,O_L_VS,MARKER,O_ZR,MARKER
Line	74		FCB	O_R_VS,O_L_ST,MARKER,O_SL,MARKER
Line	75		FCB	O_R_VS,O_L_MD,MARKER,O_SL,MARKER
Line	76		FCB	O_R_VS,O_L_WE,MARKER,O_ML,MARKER
Line	77		FCB	O_R_VS,O_L_VW,MARKER,O_ML,MARKER
Line	78		FCB	O_R_ST,O_L_VS,MARKER,O_SR,MARKER
Line	79		FCB	O_R_ST,O_L_ST,MARKER,O_ZR,MARKER
Line	80		FCB	O_R_ST,O_L_MD,MARKER,O_SL,MARKER
Line	81		FCB	O_R_ST,O_L_WE,MARKER,O_ML,MARKER
Line	82		FCB	O_R_ST,O_L_VW,MARKER,O_ML,MARKER
Line	83		FCB	O_R_MD,O_L_VS,MARKER,O_SR,MARKER
Line	84		FCB	O_R_MD,O_L_ST,MARKER,O_SR,MARKER
Line	85		FCB	O_R_MD,O_L_MD,MARKER,O_ZR,MARKER
Line	86		FCB	O_R_MD,O_L_WE,MARKER,O_SL,MARKER
Line	87		FCB	O_R_MD,O_L_VW,MARKER,O_SL,MARKER
Line	88		FCB	O_R_WE,O_L_VS,MARKER,O_MR,MARKER
Line	89		FCB	O_R_WE,O_L_ST,MARKER,O_MR,MARKER
Line	90		FCB	O_R_WE,O_L_MD,MARKER,O_SR,MARKER
Line	91		FCB	O_R_WE,O_L_WE,MARKER,O_ZR,MARKER
Line	92		FCB	O_R_WE,O_L_VW,MARKER,O_SL,MARKER
Line	93		FCB	O_R_VW,O_L_VS,MARKER,O_MR,MARKER
Line	94		FCB	O_R_VW,O_L_ST,MARKER,O_MR,MARKER
Line	95		FCB	O_R_VW,O_L_MD,MARKER,O_SR,MARKER
Line	96		FCB	O_R_VW,O_L_WE,MARKER,O_SR,MARKER
Line	97		FCB	O_R_VW,O_L_WE,MARKER,O_ZR,ENDR

```
Line 98 ; Main Program
Line 99
                 ORG $4000
Line 100: Fuzzification-------
        : Fuzzification Procedure
        ; MEM function determines grade of membership.
        ; Registers must be set up as follows:
        ; A: must hold the current crisp value of system input variable
             X: must point to 4-byte data structure describing the trapezoidal
                membership function for a label of the system input
             Y: must point to the fuzzy input (RAM location) where the resulting
                grade of membership is to be stored
        ; Perform fuzzification for right sensor
Line 101
                 LDX #R Very Strong ; Start of Input Mem func
Line 102
                 LDY #R VS
                                        ; Start of Fuzzy Mem values
Line 103
                 LDAA RSENSOR
                                           ; Right Sensor Value
Tine 104
                                           : Number of iterations
                LDAB
                       #5
Line 105
                 Loopr MEM
                                           ; Assign mem value
Line 106
                                           ; Do all five iterations
                 DBNE B, Loopr
                             Revised: Sep 1, 2004
                                                                      31
```

```
; Perform fuzzification for left sensor
Line 107 LDAA LSENSOR ; Left Sensor Value
Line 108 LDAB #5 ; Number of iterations
Line 109 Loopl MEM ; Assign mem value
Line 110 DBNE B,Loopl ; Do all five iterations
```

```
; Fuzzy Logic Rule Evaluation-----
        ; REV function performs an unweighted evaluation of a list of rules,
        ; using fuzzy input values to produce fuzzy outputs.
        ;Before executing REV, perform the following set up operations.
        ; X: must point to the first 8-bit element in the rule list.
             Y: must point to the base address for fuzzy inputs and outputs
             A: must contain the value of \$FF, and the CCR V bit must = 0
                (LDAA #$FF places the correct value in A and clears V)
           Clear fuzzy outputs to zeros
Line 111
                           ; Process rules
        LDY #R VS
Line 112
               LDX #Rule Start ; Point X to the start addr
```

: Initialize min and V bit

: Evaluate rules

Line 113

Line 114

LDAA #\$FF

REV

```
Line 115; Defuzzification Process-----
        ; WAV function performs weighted average calculations on
        ; values stored in memory.
            X: used to reference one source operand list
              Y: used to reference second source operand list
             B: used a s counter to control number of elements to
                 be included in the weighted average
Line 116
        LDX #Medium Left ; Start of output mem func
Line 117 LDY #ML
                                   ; Start of mem values
Line 118
       LDAB #$05
                                     ; Five elements sum
Line 119
       WAV
                                      ; Computing a crisp value
Line 120
                                      ; Extended divide - 32 bit/16 bit
              EDIV
Line 121
        TFR Y,D
                                      ; Store answer to D
Line 122
           STAB CONTROLS
                                    ; Save the answer
Line 123
               END
```